



12/12/08

This procedure is used to update Main CPU flash programming for FTdx9000 transceivers that have already been updated to PEP9000.

IMPORTANT: This procedure is only needed under the below conditions:

- Must have the PEP9000 logo sticker on the radio below the serial number label.



- Must have Version V0505 or higher. While holding the three buttons [GEN]+[50]+[ENT] turn the radio on and read the last 3 digits on the top line of the LED display. See page (3) for more detail instructions. If the software version is not immediately displayed, your radio has not been updated to PEP9000; you must have the radio updated. Please contact Vertex Standard, Amateur Tech Support.

If your radio meets the above conditions you may proceed to update the main CPU to V0509 programming. (If you already have V0509 no update is needed).

We recommend installing the Flash Programming Software on a PC computer with Windows 2000, XP or Vista Operating System; and use the CT-119 programming cable

The update software is available from our website at <http://www.yaesu.com>. The CT-119 programming cable is available from your authorized Vertex Standard dealer. You may also order by email to Vertex Standard parts department, yaesuparts@vxstdusa.com

Ver. 0509 implements improvements (also includes previous Ver. 0508 updates):

- Add MENU #022 LEVEL Indicator for PITCH•SPEED•CONTOUR•NOTCH•DNR•CW DELAY•VOX DELAY (Press the [ENT] key to set the command to “ON” or “OFF”)
- Add MENU #036 CAT data Indicator (ENABLE/DISABLE)
- Add the CAT Command (CO) for APF, ON
- CAT commands are changed.
FT0, FT1: simplex/split (toggle)
FT2: SIMPLEX
FT3: SPLIT
- Mu TUNE Bar display (above the main VFO) is improved (Menu 16, uTUNE option).
The center indicator should disappear if the frequency is out of the amateur band.

*The software updates will work with **PEP9000** all versions (AF, AS, EU, NA, OC, SA or all Countries) of the FTdx9000Contest, FTdx9000D and FTdx9000MP*

- (5) Now go to the desktop and find the **FSW004** as shown below. Double-click the **FSW004** icon, displayed on the Program Screen.



- (6) When the program opens, confirm that the file **AH010_V0509.SFL** is highlighted; if not, click on it to highlight it.
- (7) Click on [WRITE] in the program window. A green status bar should appear below the [WRITE] button to show the progress of the download. Do not interrupt the process until it completes.
- (8) When the loading process is complete, an [OK?] box will appear. Click [OK?].
- (9) Turn off the main power switch. Located on the rear panel of the FTdx9000 (or on the top of the power supply for the FTdx9000MP). Remove the CT-119 cable from the **DB-9F connector** of your computer and the **ACC** connector on the rear of the transceiver.
- (10) Turn on the main power switch located on the back of the FTdx9000 (or on the top of the power supply for FTdx9000MP).
- (11) Press and hold in the [FAST] and [LOCK] keys while turning the radio back on. (This resets the radio and locks in the new software.) The updating process is now complete. You may need to enter your custom menu settings now.

The software version can be displayed on the radio

While holding the three buttons [GEN]+[50]+[ENT] turn the radio on. Confirm the new version software is displayed in the VFO-A window for 5 seconds, **11.245.09** (EDSP V11.24, Main V0509). Then the radio will start up in normal operation.



We hope this new software will increase your enjoyment of your FTdx9000. Thank you for choosing Yaesu radios. If you have any problems or questions please contact Vertex Standard, Amateur Tech Support. amateurtech@vxstdusa.com

Best regards,

Mikio Maruya, WA6F
Executive Vice President
Amateur Radio, Engineering & Customer Service
Vertex Standard USA, Inc.